

Homework #10: ECE 461/661

z-Transforms, s to z conversion, Root Locus in the z-Domain. Due Monday, November 13th

z-Transforms

1) Determine the difference equation that relates X and Y

$$Y = \left(\frac{0.05z(z-1)}{(z-0.9)(z-0.8)(z-0.5)} \right) X$$

2) Determine y(k) assuming

$$Y = \left(\frac{0.05z(z-1)}{(z-0.9)(z-0.8)(z-0.5)} \right) X \quad x(t) = 2 \cos(4t) + 3 \sin(4t)$$
$$T = 0.01$$

3) Determine y(k) assuming

$$Y = \left(\frac{0.05z(z-1)}{(z-0.9)(z-0.8)(z-0.5)} \right) X \quad x(k) = u(k)$$

s to z conversion

4) Determine the discrete-time equivalent of G(s). Assume T = 0.1 seconds

5) Determine the discrete-time equivalent of G(s). Assume T = 0.01 seconds

$$G(s) = \left(\frac{2331}{(s+2.6338)(s+30.2062)(s+53.7896)} \right)$$

Root Locus in the z-Domain

Assume T = 0.01 seconds. (change)

$$G(s) = \left(\frac{2331}{(s+2.6338)(s+30.2062)(s+53.7896)} \right)$$

6) Draw the root locus for G(z)

7) Find k for no overshoot in the step response

- Simulate the closed-loop system's step response

8) Find k for 20% overshoot for a step response (damping ratio = 0.4559)

- Simulate the closed-loop system's step response

9) Find k for a damping ratio of 0.00

- Simulate the closed-loop system's step response